

NTE1468 Integrated Circuit Audio, Low Power Output Amplifier

Applications:

- Line Output Amplifier
- Recording Head Driver and Headphone Driver of Tape Recorder Deck.

Features:

- Low Noise: $V_{NI} = 1\mu V_{rms}$
- Wide Operating Supply Voltage Range: $V_{CC} = 3.5$ to $25V$
- 150mW Audio Output Power at $V_{CC} = 20V$, $R_L = 150\Omega$

Absolute Maximum Ratings: ($T_A = +25^\circ C$ unless otherwise specified)

| | |
|--|-------------------------------|
| Supply Voltage, V_{CC} | 25V |
| Power Dissipation, P_D | 400mW |
| Derated Above $25^\circ C$ | 4mW/ $^\circ C$ |
| Operating Temperature Range, T_{opr} | -25° to $+75^\circ C$ |
| Storage Temperature Range, T_{stg} | -55° to $+125^\circ C$ |

Electrical Characteristics: ($V_{CC} = 20V$, $T_A = +25^\circ C$, $R_L = 150\Omega$, $R_f = 600\Omega$, $f = 1kHz$ unless otherwise specified)

| Parameter | Symbol | Test Conditions | Min | Typ | Max | Unit |
|--------------------------------|-------------|---------------------------------------|------|------|------|---------------|
| Operating Supply Voltage Range | V_{CCopr} | | 3.5 | 20 | 25 | V |
| Supply Current | I_{CC} | $f = 1kHz, V_{OUT} = 0$ | – | 4.0 | 6.0 | mA |
| | | $f = 1kHz, V_{OUT} = 4.5V_{rms}$ | – | 16.5 | – | mA |
| Voltage Gain (Open Loop) | G_{VO} | $R_f = 0\Omega$ | – | 63 | – | dB |
| Voltage Gain (Closed Loop) | G_V | Note 1 | 36.5 | 40.0 | 43.5 | dB |
| Total Harmonic Distortion | THD | $V_{OUT} = 4.5V_{rms}$ | – | 0.5 | 1.0 | % |
| | | $V_{CC} = 6.5V, V_{OUT} = 1.0V_{rms}$ | – | 1.0 | – | % |
| Maximum Output Voltage | V_{OM} | THD = 10% | – | 6 | – | V_{rms} |
| Input Resistance | R_{IN} | | – | 30 | – | k Ω |
| Output Noise Voltage | V_{NO} | BW = 20Hz to 20kHz, $R_g = 1k\Omega$ | – | 100 | 200 | μV_{rms} |

Note 1. In regard to the value of voltage gain (closed loop), it is possible to be classified.

Pin Connection Diagram (Front View)

