



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089

NTE1711 Integrated Circuit 2 Head Recording Amp for VCR

Description:

The NTE1711 is an integrated circuit in a 9-Lead SIP type package designed for use as a recording amplifier in VCRs.

Functions:

- Mixer Circuit
- Recording Current Amplifier

Features:

- Video Head can be a Driver
- Supply Voltage of Either 9V or 12V

Absolute Maximum Ratings: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Supply Voltage, V_{CC} 14.4V
 Power Dissipation, P_D 600mW
 Operating Ambient Temperature Range, T_{opr} -20° to $+70^\circ\text{C}$
 Storage Temperature Range, T_{stg} -40° to $+150^\circ\text{C}$

Note 1. Operating Supply Voltage Range: $V_{CC(opr)} = 7.8\text{V}$ to 13V .

Electrical Characteristics: ($T_A = +25^\circ\text{C} \pm 2^\circ\text{C}$, $V_{CC} = 9\text{V}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Total Circuit Current	I_{tot}		22	–	34	mA
Output Amplitude	v_o	$V_i = 50\text{mV}_{P-P}$	10	–	20	mV_{P-P}
2nd Harmonic Distortion	D_{2f}	$I_O = 15\text{mA}_{P-P}$	–	–	–35	dB
3rd Harmonic Distortion	D_{3f}	$I_O = 15\text{mA}_{P-P}$	–	–	–40	dB
Crosstalk	CT	$I_O = 15\text{mA}_{P-P}$	–	–	–35	dB
Cross Modulation	CM1	$I_O = 15\text{mA}_{P-P}$	–	–	–35	dB
	CM2	$I_O = 15\text{mA}_{P-P}$	–	–	–40	dB

Pin Connection Diagram
(Front View)

