



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089

NTE1775 Integrated Circuit PIF Subsystem for TV Receiver

Description:

The NTE1775 is a picture IF subsystem that provides 3-stage IF amplifier, Video Detector, black and white noise inverting circuits and AFT detector for a TV receiver.

The NTE1775 also provides internal fast response AGC with dual time constants for the IF amplifier stages and delayed AGC for an external RF amplifier stage. It is designed for FET top front-end (reverse AGC).

Features:

- High Input Sensitivity 3-Stage IF Amplifier: 58.75MHz 100µV_{RMS} Type
- Gain Reduction with Excellent Stability: Reduction Range 65dB Typ
- Video Detector with Linear Characteristics
- Black and White Noise Inverting Circuits
- Balanced AFT Output
- Improved Fast AGC Response
- Delayed AGC Output for a Front-End FET Top Front-End
- Minimal External Components and Adjustments Required

Absolute Maximum Ratings: (T_A = +25°C unless otherwise specified)

Supply Voltage (Pin11), V _{CC}	15V
Open Loop Voltage (Pin14), V ₁₄	15V
Video DC Output Current (Pin12), I ₁₂	6mA
Power Dissipation , P _D	1.4W
Derated Above 25°C	11.2mW/°C
Operating Temperature Range, T _{opr}	-20° to +65°C
Storage Temperature Range, T _{stg}	-55° to +150°C

Electrical Characteristics: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Recommended Supply Voltage	V_{CC}		10.8	12.0	13.2	V
Supply Current	I_{CC}	$V_{CC} = 12\text{V}$	42	51	63	mA
Video DC Output Voltage	V_{12}	$V_{CC} = 12\text{V}$	5.2	5.5	5.8	V
AFT DC Output Voltage	V_5	$V_{CC} = 12\text{V}$, SW ₁ : ON, SW ₂ : ON	5.3	6.8	8.3	V
	V_6	$V_{CC} = 12\text{V}$, SW ₁ : ON, SW ₂ : ON	5.3	6.8	8.3	V
AFC Output Offset Voltage	$V_5 - V_6$	$V_{CC} = 12\text{V}$, SW ₁ : ON, SW ₂ : ON	-1.5	0	+1.5	V
RF AGC Residual Output Voltage	$V_4 \text{ SAT}$	$V_{CC} = 12\text{V}$, SW ₃ : 2, SW ₄ : 1	-	-	0.5	V
RF AGC Leakage Current	$I_4 \text{ LEAK}$	$V_{CC} = 12\text{V}$, SW ₃ : 1, SW ₄ : 1	-	-	1.0	μA
Video Sensitivity		$V_{CC} = 12\text{V}$, $V_{12} = 0.8V_{P-P}$, $f_p = 58.75\text{MHz}$, AM: 30%	50	100	220	μV_{rms}
AGC Range	$\Delta A \text{ (IF)}$	$V_{CC} = 12\text{V}$, $f_p = 58.75\text{MHz}$, $V_{14} = 11.5\text{V}$ to 4.0V	60	65	-	dB
Sync Tip Level Voltage	V_{SYNC}	$V_{CC} = 12\text{V}$, $f_p = 58.75\text{MHz}$	2.3	2.5	2.7	V
Maximum Input Voltage	$V_{\text{IN Max}}$	$V_{CC} = 12\text{V}$, $f_p = 58.75\text{MHz}$	100	120	-	mV_{rms}
White Noise, Threshold Level	$V_{W \text{ TH}}$	$V_{CC} = 12\text{V}$, $f_p = 58.75\text{MHz}$	6.0	6.4	6.8	V
White Noise, Clamp Level	$V_{W \text{ CL}}$	$V_{CC} = 12\text{V}$, $f_p = 58.75\text{MHz}$	3.7	4.1	4.5	V
Black Noise, Threshold Level	$V_{B \text{ TH}}$	$V_{CC} = 12\text{V}$, $f_p = 58.75\text{MHz}$	1.4	1.6	1.8	V
Black Noise, Clamp Level	$V_{B \text{ CL}}$	$V_{CC} = 12\text{V}$, $f_p = 58.75\text{MHz}$	2.9	3.3	3.7	V
Video Frequency Response	f_{BW}	$f = 58.75\text{MHz}$, Sweep Generator	4.5	5.5	-	MHz
Carrier Suppression	CL	SG ₁ = $100\text{mV}_{\text{rms}}$, SG ₂ , SG ₃ : OFF	40	50	-	dB
2 nd Carrier Suppression	$I_{2\text{nd}}$	SG ₁ = $100\text{mV}_{\text{rms}}$, SG ₂ , SG ₃ : OFF	40	50	-	dB
920kHz Carrier Beat Suppression	I_{920}	SG ₁ = $100\text{mV}_{\text{rms}}$, SG ₂ = 32mV_{rms} , SG ₃ = 32mV_{rms}	33	38	-	dB
Differential Phase	DP		-	3.5	5.0	deg
Differential Gain	DG		-	7	10	%
Input Impedance	R_{IN}	$f = 58.75\text{MHz}$ Between Pin1 and Pin16	3.0	4.5	6.0	$\text{k}\Omega$
	C_{IN}		-	2.0	5.0	pF
AFT Sensitivity		$f = 58.75\text{MHz}$	-	16	-	kHz/V
AFT Output Upper Voltage	$V_5, V_6 \text{ U}$	$f = 58.75\text{MHz}$	11.7	11.9	12.0	V
AFT Output Lower Voltage	$V_5, V_6 \text{ L}$	$f - 58.75\text{MHz}$	1.8	2.3	2.8	V
Maximum Available Current	$I_4 \text{ Max}$		0.3	-	-	mA

Pin Connection Diagram

