



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089

NTE1780 Integrated Circuit 2 Channel Tone/DC Volume/Balance Control Circuit

Description:

The NTE1780 is an integrated circuit in a 12-Lead SIP type package designed for 2-channel volume and tone control circuits.

Features:

- Easier Compact Set Design
- Functions Are: 2-Channel Bass, Treble Control Circuit
- Balance Control Circuit
- DC Volume Control Circuit (Volume Control ^w/Physiological Characteristics)
- All Functions Enable DC Controllable

Absolute Maximum Ratings: (T_A = +25°C unless otherwise specified)

Supply Voltage, V _{CC}	14.4V
Circuit Voltage, V _{1, 4, 5, 6-7, V_{8, 9, 11, 12-7}}	0, V ₂₋₇
Supply Current, I ₂	64mA
Circuit Current, I _{3, I₁₀}	-40mA
Power Dissipation, P _D	920mW
Operating Ambient Temperature Range, T _{opr}	-20° to +70°C
Storage Temperature Range, T _{stg}	-55° to +150°C

Electrical Characteristics: (T_A = +25C, V_{CC} = 12V unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Circuit Current	I _{tot}	V _{CC} = 12V	24	38	50	mA
Circuit Voltage	V _{3, 10-7}	V _i = No Signal, V ₁₂ = V _{CC} , V ₁ = V ₅ = V ₈ = V _{CC} /2	8.0	8.4	8.8	V
Volume Circuit						
Maximum Output	V _{Omax}	f = 1kHz, V _i = 400mV _{rms} , V ₁₂ = V _{CC} , V ₁ = V ₅ = V ₈ = V _{CC} /2	190	230	270	mV _{rms}
Channel Balance (Note 1)	CB		-	+0.2	±1.0	
Volume Starting Voltage	V _(st)	f = 1kHz, V _i = 400mV _{rms} , V ₁₂ = VR, V ₁ = V ₅ = V ₈ = V _{CC} /2, Note 2	0.40	0.60	0.90	V
Residual Tone Level (Volume Minimum)	V _{min.}	f = 1kHz, V _i = 400mV _{rms} , V ₁₂ = 0, V ₁ = V ₅ = V ₈ = V _{CC} /2	-	25	50	μV _{rms}
Balance Control Circuit						
Attenuation (R-ch)	A _{ttBR}	f = 1kHz, V _i = 400mV _{rms} , V ₁₂ = V _{CC} , V ₅ = V ₈ = V _{CC} /2, V _{OR1} : V ₁ = (5.5/12), V _{CC} (VR-1), V _{OR2} : V ₁ = 0V, Note 3	-32	-45	-	dB

Note 1. Deviation between R and L-ch for maximum output.

Note 2. V₁₂ voltage when output voltage is 0.1mV_{rms}.

Note 3. A_{ttBR}: V_{OR2}/V_{OR1}

Electrical Characteristics (Cont'd): ($T_A = +25^\circ\text{C}$, $V_{CC} = 12\text{V}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Balance Control Circuit (Cont'd)						
Attenuation (L–ch)	A_{ttBL}	$f = 1\text{kHz}$, $V_i = 400\text{mV}_{\text{rms}}$, $V_{12} = V_{CC}$, $V_5 = V_8 = V_{CC}/2$, $V_{\text{OR1}}: V_1 = (6.5/12)$, $V_{CC}(\text{VR}-1)$, $V_{\text{OR2}}: V_1 = 0\text{V}$, Note 4	-32	-45	-	dB
Tone Control Circuit						
Low Frequency Boost Control	V_{40}/V_{1k}	$V_{1k}: f = 1\text{kHz}$, $V_i = 400\text{mV}_{\text{rms}}$ Output voltage when $V_{12} = V_{CC}$, $V_1 = V_5 = V_8 = V_{CC}/2$ $V_{40}: f = 40\text{Hz}$, $V_i = 400\text{mV}_{\text{rms}}$ Output voltage when $V_{12} = V_{CC}$, $V_5 = V_8 = V_{CC}$	8	10	12	dB
Low Frequency Cut Control	V_{40}/V_{1k}	$V_{1k}: f = 1\text{kHz}$, $V_i = 400\text{mV}_{\text{rms}}$ Output voltage when $V_{12} = V_{CC}$, $V_1 = V_5 = V_8 = V_{CC}/2$ $V_{40}: f = 40\text{Hz}$, $V_i = 400\text{mV}_{\text{rms}}$ Output voltage when $V_{12} = V_{CC}$, $V_5 = V_8 = V_{CC}$	-7.5	-12.0	-16.0	dB
High Frequency Boost Control	V_{15}/V_{1k}	$V_{1k}: f = 1\text{kHz}$, $V_i = 400\text{mV}_{\text{rms}}$ Output voltage when $V_{12} = V_{CC}$, $V_1 = V_5 = V_8 = V_{CC}/2$ $V_{15}: f = 15\text{kHz}$, $V_i = 400\text{mV}_{\text{rms}}$ Output voltage when $V_{12} = V_{CC}$, $V_5 = V_8 = V_{CC}$	7.5	10.0	13.0	dB
High Frequency Cut Control	V_{40}/V_{1k}	$V_{1k}: f = 1\text{kHz}$, $V_i = 400\text{mV}_{\text{rms}}$ Output voltage when $V_{12} = V_{CC}$, $V_1 = V_5 = V_8 = V_{CC}/2$ $V_{15}: f = 15\text{kHz}$, $V_i = 400\text{mV}_{\text{rms}}$ Output voltage when $V_{12} = V_{CC}$, $V_5 = V_8 = V_{CC}$	-7.5	-12.0	-18.0	dB
Crosstalk	CT	$f = 1\text{kHz}$, $V_i = 400\text{mV}_{\text{rms}}$, $V_{1q2} = V_{CC}$, $V_1 = V_5 = V_8 = V_{CC}/2$	-65	-80	-	dB
Output Noise Voltage	V_{no}	$V_i = \text{No Signal}$, $V_{12} = V_{CC}$, $V_1 = V_5 = V_8 = V_{CC}/2$	-	80	120	μV_{rms}
Distortion Rate	THD	$f = 1\text{kHz}$, $V_i = 400\text{mV}_{\text{rms}}$, $V_{12} = V_{CC}$, $V_1 = V_5 = V_8 = V_{CC}/2$	-	0.2	0.5	%
Input Resistance	R_i (6), (9)	$f = 1\text{kHz}$	8.2	11.0	13.5	$\text{k}\Omega$
	R_i (4), (11)		11.0	16.0	22.0	$\text{k}\Omega$
Output Resistance	R_o (3), (10)	$f = 1\text{kHz}$	60	110	160	Ω

Note 4. $A_{\text{ttBL}}: V_{\text{OL2}}/V_{\text{OL1}}$

Pin Connection Diagram
(Front View)



