



ELECTRONICS, INC.  
 44 FARRAND STREET  
 BLOOMFIELD, NJ 07003  
 (973) 748-5089  
<http://www.nteinc.com>

## NTE1811 Integrated Circuit Cylinder Interface Circuit for VCR

**Features:**

- PG Monostable Multivibrator
- Tracking Monostable Multivibrator
- CTL Amplifier
- Supply Voltage: 5V

**Absolute Maximum Ratings:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Supply Voltage,  $V_{CC}$  ..... 6.0V  
 Power Dissipation ( $T_A = +70^\circ\text{C}$ ),  $P_D$  ..... 100mW  
 Operating Ambient Temperature Range,  $T_{opr}$  .....  $-20^\circ$  to  $+70^\circ\text{C}$   
 Storage Temperature Range,  $T_{stg}$  .....  $-40^\circ$  to  $+150^\circ\text{C}$

**Electrical Characteristics:** ( $V_{CC} = 5\text{V}$ ,  $T_A = +25^\circ\text{C}$ ,  $V_{cc(opr)} = 4.5$  to  $5.5\text{V}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Circuit Current	$I_{11}$	Without Load	7.0	-	14	mA
CY. PG. FG. Input Sensitivity	$S_{17,16}$		-	-	1.5	V
PG MM Delay Time	$T_{15}$	$C = 0.056\mu\text{F}$ , $R = 20\text{k}\Omega$	690	-	860	$\mu\text{s}$
H/SW Output High	$V_{OH14}$	Without Load	4.6	-	-	V
H/SW Output Low	$V_{OL14}$		-	-	0.4	V
1/2 $V_{SS}$ Input Sensitivity	$S_{10}$		-	-	1.5	V
Rec. Start Select Sensitivity	$S_9$		3.0	-	-	V
For./Rev Start Select Sensitivity	$S_4$		3.0	-	-	V
Rec. CTL Output High	$V_{OH6}$	Without Load	4.0	-	-	V
Rec. CTL Output Low	$V_{OL6}$		-	-	0.4	V
PB CTL Amp. Gain (For.)	$G_{(forward)}$		60	-	72	dB
PB CTL Amp. Gain (Rev.)	$G_{(reverse)}$		59	-	72	dB
Tracking Mono. Multi. Delay Amount	$T_{13}$	$C = 0.27\mu\text{F}$ , $R = 100\text{k}\Omega$	18	-	22	ms
PB CTL Wave Shaping Input Sensitivity	$S_2$		300	-	-	mV

### Pin Connection Diagram

