



RoHS
2002/95/EC

ELECTRONICS, INC.
44 FARRAND STREET
BLOOMFIELD, NJ 07003
(973) 748-5089
<http://www.nteinc.com>

NTE7185 **Integrated Circuit** **Vertical Deflection Booster for** **Monitors and High Performance TVs**

Description:

The NTE7185 was designed for use in monitors and high performance televisions. This device can handle flyback voltage up to 70V. More than this it is possible to have a flyback voltage which is more than the double of the supply (Pin2). This allows to decrease the power consumption or to decrease the flyback time for a given supply voltage.

Features:

- Power Amplifier
- Thermal Protection
- Output Current up to 3.0A_{PP}
- Flyback Voltage up to 70V (On Pin5)
- Suitable for DC Coupling Application
- External Flyback Supply

Absolute Maximum Ratings:

| | |
|---|------------------------|
| Supply Voltage (Pin2, Note 1), V _S | 40V |
| Flyback Peak Voltage (Pin6, Note 1) | 75V |
| Amplifier Input Voltage (Pin thru Pin7, Note 1) V ₁ , V ₇ | -0.3V + V _S |
| Maximum Output Peak Current (Note 2), I _O | 2.5A |
| Maximum Sink Current (t < 1ms), I ₃ | 2.5A |
| Maximum Source Current (t < 1ms), I ₃ | 2.5A |
| ESD Susceptibility, V _{ESD} | |
| Tool Model (Note 3) | 300V |
| Human Model (Note 4) | 2kV |
| Voltage Difference between Flyback Supply and Supply Voltage, V ₃ – V ₂ | 50V |
| Minimum Voltage (Note 1), V ₃ , V ₅ , V ₆ | -0.4V |
| Operating Ambient Temperature Range, T _{oper} | -20° to +75°C |
| Storage Temperature Range, T _{stg} | -40° to +150°C |
| Junction Temperature, T _j | +150°C |
| Maximum Thermal Resistance, Junction-to-Case, R _{thJC} | 3°C/W |
| Temperature for Thermal Shutdown, T _t | 150°C |
| Hysteresis on T _t , ΔT _t | 10°C |
| Recommended Maximum Junction Temperature, T _{jr} | 120°C |

Note 1. Versus Pin4.

Note 2. The output current can reach 4A peak for 10μs (up to 120Hz).

Note 3. Equivalent to discharging a 200pF capacitor through a 0Ω series resistor.

Note 4. Equivalent to discharging a 150pF capacitor through a 1.5Ω series resistor.

Electrical Characteristics: ($V_S = 35V$, $T_A = 25^\circ C$, unless otherwise specified)

| Parameter | Symbol | Test Conditions | Min | Typ | Max | Unit |
|---|--------------------|------------------------|-------|------|-----|------------------|
| Operating Supply Voltage Range | V_S | | 10 | - | 35 | V |
| Operating Flyback Supply Voltage | V_{3M} | | V_S | - | 70 | V |
| Quiescent Current (Pin2) | I_2 | $I_3 = 0, I_5 = 0$ | - | 10 | 20 | mA |
| Quiescent Current (Pin6) | I_6 | $I_3 = 0, I_5 = 0$ | - | 25 | 35 | mA |
| Max. Scanning Peak Output Current | I_o | | - | - | 1.5 | A |
| Amplifier Bias Current | I_1 | $V_1 = 20V, V_7 = 21V$ | - | -0.4 | -2 | μA |
| Amplifier Bias Current | I_7 | $V_1 = 21V, V_7 = 20V$ | - | -0.4 | -2 | μA |
| Offset Voltage | V_{10} | | - | 0 | 7 | mV |
| Offset Drift versus Temperature | $\Delta V_{10}/dt$ | | - | -10 | - | $\mu V/^\circ C$ |
| Voltage Gain | GV | | 80 | - | - | dB |
| Output Saturation Voltage to GND (Pin4) | V_{5L} | $I_5 = 1.5A$ | - | 1.0 | 2 | V |
| Output Saturation Voltage to Supply (Pin6) | V_{5H} | $I_5 = -1.5A$ | - | 1.7 | 2.5 | V |
| Diode Forward Voltage between Pin5 & Pin6 | V_{D5-6} | $I_5 = 1.5A$ | - | 1.5 | 2.1 | V |
| Diode Forward Voltage between Pin3 & Pin6 | V_{D3-6} | $I_3 = 1.5A$ | - | 2.3 | 3 | V |
| Voltage Drop between Pin3 & Pin6 (2nd part of flyback) | V_{3-6} | $I_3 = -1.5A$ | - | 4 | 5 | V |

Pin Connection Diagram
(Front View)



